AutoKarnet

Honda Forza 300 / 350 330 maintenance sheet

Forza 350 · 29 PS (21 kW)

Years : 2021–present Generated on : 04 November 2026

Technical specifications

Petrol | Engine code : Honda 330 eSP+ | 330 cm³ | Automatic variator (CVT)

Maintenance schedule

≈: estimated reference — the vehicle's service indicator prevails.

ITEM	INTERVAL	
Oil and filter change	**≈ 12,000 km or 1 year**	JASO MA or MA2 approved four-stroke motorcycle oil (JASO MB on scooters): an "energy conserving" car oil makes the wet clutch slip. Change it more often in city use or on track.
Brake fluid	**Every 2 years**	Replace the fluid in both circuits (and the hydraulic clutch if fitted), whatever the mileage; dark fluid has absorbed moisture.
Fork oil	**≈ 30,000 km**	Fork oil change and seal check; an oil film on the tubes means a seal needs replacing before it contaminates the brake caliper.
Final drive oil	**≈ 20,000 km**	The rear-wheel gearcase has its own oil, separate from the engine oil; replace it when the service book says, often with the variator belt.
Spark plugs	**Every 16,000 km**	Replace the full set; worn plugs raise consumption and cause misfires.
Air filter	**Every 16,000 km**	Replace more often in dusty conditions.
Valve clearance	**Every 16,000 km**	Check and adjust if needed, often together with the plugs; too little clearance burns the valves, too much makes the engine noisy.
Variator belt and rollers	**Every 24,000 km**	Replace the belt and check the rollers and clutch; a worn belt makes the scooter slip and can snap while riding.
Coolant	**Every 3 years**	Replace the coolant and check the hoses and radiator; check the level cold between services.

Service record

DATE	MILEAGE	WORK DONE	WORKSHOP

Indicative intervals and costs: adapt maintenance to the engine, use and manufacturer’s instructions.

Full schedule and updates : https://auto-karnet.com/en/maintenance/honda/forza-350/forza-350-2021/330-29